

ROTAPULS • ROTACOD

Wire actuated transducer for encoders

www.lika.biz



CK58



AMC58



AMC58 PB

SF SUITABLE ENCODERS*

* Also all CK58, ASC58 and AMC58 series with \varnothing 15 mm hollow shaft

Series	Resolution	Output	"L" see drawing
CK58-H-500ZCU415R	0,4 mm (x4 = 0,1)	PP/LD Universal circuit	~ 42 mm
CK58-H-2000ZCU415R	0,1 mm	PP/LD Universal circuit	~ 42 mm
AMC5812/4096GS-15 + E10MLS	~ 0,049 mm	SSI	~ 80 mm
AMC5812/4096PB-15 + CC-PB	0,1 mm*	Profibus	~ 80 mm

*Programmed resolution by the customer at 2000 counts/rev.



I58



AS58



AS58 PB

SAK SUITABLE ENCODERS*

* Also all I58, AS58 and AS58 series with \varnothing 6 mm shaft

Series	Resolution	Output	"L" see drawing
I58-H-3000ZCU46RL2	0,1 mm	PP/LD Universal circuit	~ 42 mm
I58-H-3000ZCZ46R + EPFL121	0,1 mm	PP/LD Universal circuit	~ 42 mm
AM5812/4096PS-6 + EPFL121	0,1 mm*	SSI programmable	~ 80 mm
AM5812/4096GS-6 + E10MLS	~ 0,073 mm	SSI	~ 80 mm
AM5812/4096PB-6 + CC-PB	0,1 mm*	Profibus	~ 80 mm

*Programmed resolution by the customer at 3000 counts/rev.



I58



AS58



AS58 PB

SBK SUITABLE ENCODERS*

* Also all I58, AS58 and AS58 series with \varnothing 6 mm shaft

Series	Resolution	Output	"L" see drawing
I58-H-1250ZCU46RL2	0,4 mm (x4 = 0,1)	PP/LD Universal circuit	~ 42 mm
I58-H-5000ZCZ46R + EPFL121	0,1 mm	PP/LD Universal circuit	~ 42 mm
AM5813/4096PS-6 + EPFL121	0,1 mm*	SSI programmable	~ 80 mm
AM5813/4096GS-6 + E10MLS	~ 0,061 mm	SSI	~ 80 mm
AM5813/4096PB-6 + CC-PB	0,1 mm*	Profibus	~ 80 mm

*Programmed resolution by the customer at 5000 counts/rev.